

# AH-0817

## Resettable Manual Call Point




### Features

- Red LED with current limiting resistor.
- Three different resistance selectable (270, 470, 680 ohm).
- Choice of red, yellow, blue or green finish also available for custom-made.
- Clear protection cover is also available (optional).

### Specifications

Model	AH-0817
Operating Contact	6A 125/250VAC
Resistance	30mΩ
Ambient Temperature	-25°C ~ +85°C
Dimensions	87.5mm (H) x 87.5mm(W) x 54mm (D)
Weight	About 145g

### Wiring



### Jumper Selections

J1	J2	J3	
			Clean normally open contact - No LED possible
			Blocking diode selected - No LED possible
			Used for future application
			270 ohm resistor selected - LED illuminates when the call point is activated
			470 ohm resistor selected - LED illuminates when the call point is activated
			680 ohm resistor selected - LED illuminates when the call point is activated

EN54  

Distributor in Vietnam:

**VIET BAO FIREFIGHTING AND PREVENTING EQUIPMENT COMPANY LIMITED.**



140 Nguyen Van Thu St (Ground floor), DaKao ward, Dist.1, HCMC.

Tel: 84.28.39101156 – 39101157. Fax: 84.28.39101158

Email: vietbao@vietbaopccc.com.vn Website: <http://vietbaopccc.com.vn>